



# Smart controller

SHENZHEN CL LIGHTING TECHNOLOGY CO., LTD  
Address: Block B, 4th industrial zone, Shidian Town, Baoding District, Shenzhen, China.

TEL:+86-755-27643784 / 36959611 | FAX:+86-755-27655433  
Email:cl@banqcn.com | Website: www.cl-light.com



## Product feature

- » Bluetooth APP control, RGB three-color changed and brightness adjustment, change CCT and music control function; timing function; gradual change function; circadian rhythm; camera color; APP control ;
- » The connection gateway can control the distance without restrictions;
- » It can be controlled by Bluetooth APP group, no limited the member, remote control as well.
- » It can be controlled for each group;



# CL-CIN08-Parameters

Item.NO	Colour	Input Voltage	Power	Current:	Connection	Working temperature	Dimension (mm)
CL-CIN06-01	RGBWW	12~24Vdc	Max. 240W	2A*5CH Max.4A	Bluetooth	-20°C~45°C	85.5×39×21.3
CL-CIN06-02	RGBW	12~24Vdc	Max. 240W	2A*4CH Max.4A	Bluetooth	-20°C~45°C	85.5×39×21.3
CL-CIN06-03	RGB	12~24Vdc	Max. 240W	2A*3CH Max.4A	Bluetooth	-20°C~45°C	85.5×39×21.3
CL-CIN06-04	W-WW	12~24Vdc	Max. 240W	2A*2CH Max.4A	Bluetooth	-20°C~45°C	85.5×39×21.3
CL-CIN06-05	W	12~24Vdc	Max. 240W	2A*1CH Max.4A	Bluetooth	-20°C~45°C	85.5×39×21.3

## Wiring diagram



